

HPR3321 DVB-S/S2 HD Set Top Box



Main Features

- DVB-S2X/DVB-S2/S set top box compliant with MPEG2 and MPEG4 and H.264 and H.265 and AVS+.
- Support CA condition receiving system, Dexin, Kingvon, NSTV, Sumavision, etc.
- Compatible with HDTV channels and equipped with HDMI connector, High-performance achieve from standard definition to high definition full forwarding smoothly.
- Support QPSK, 8PSK, 16APSK&32APSK demodulation mode.
- Auto search & Blind search & network search function.
- Support new version software upgrading via OTA and USB mode.
- Support customized options. Logo in boot screen, logo in STB and package.

Key Parameters

Signal CH standard	DVB-S2X Satellite signal
Input Frequency	950MHz-2150MHz
Demodulation mode	QPSK, 8PSK, 16APSK&32APSK
Symbol rate	1.0~45MSps
Video decoding	MPEG-2MP@ML/MPEG-4SP@ASP/H.263/H.264/H.265 (Optional)
Video output	1080p50/1080i/720p/576p
Voice decoding	MPEG-1Layer1&2/MPEG-2/AAC/AC3/RA/WMA
Voice mode	Left CH, right CH, stereo
Flash memory	64M bits
RAM memory	512M bits/1G bits (Optional)
Panel display	3 LED Indicator, Power Red LED, Lock Green LED
Panel button	CH+, CH-
RF input	English F-Female
Voice Vedio output	RCA out (CVBS, Audio L/R)
HD MI output	HDMI v1.4a
USB interface	1xUSB2.0 host device
Power consumption	3-5W
STB Dimension	140*83*32mm



Assessories

- AV Cable Or HDMI Cable (Optional)
- Learning remote controller (AAA prepared by customer)
- Power adaptor, 12V/1A, UK, US, EU plug (Optional).

