

Lux / Light Meter LX801

Features:

- * separate Light Sensor makes convenient testing
- * Auto-Range and Auto Zero-Adjustment
- * Large LCD, Big Digits
- * Data-Hold
- * LSI-Circuit to high reliability and durability
- * Low in power consumption
- * Low battery indication

Specifications:

Range: 0 - 50,000 LUX

Accuracy: $\pm 5.0\%$

Resolution: 0-1,999lux	1 LUX
2,000 - 19,999lux	10 lux
20,000 - 50,000 lux	100lux

Sampling time: 0.4 second

Light sensitivity: At a wave length 500-640nm Max.

General Info :

Size : 116*70*29mm

Color : Gray

Weight : 300g

Battery : 9v, 6F22 Battery

